

# K30 TWIN 2.0 HYBRID

---

## PREVENTIVE MAINTENANCE



[www.mahlkoenig.de](http://www.mahlkoenig.de)

## **K30 TWIN 2.0 HYBRID** RECOMMENDED SPARE PARTS LIST

---

<b>AMOUNT</b>	<b>DESCRIPTION</b>	<b>ARTICLE NUMBER</b>
2	Hopper incl. lid	<b>700471</b>
1	Display	<b>104014</b>
1	Burrs, espresso	<b>306715</b>
1	Burrs, filter	<b>103631</b>
2	Capacitor 25 µF 450 VAC, (for built-in grinder 100 - 127 V)	<b>309653</b>
2	Capacitor 16 µF 400 VAC, (for built-in grinder 220 - 240 V)	<b>308486</b>
2	Micro switch, service pack	<b>700448</b>
2	Fan, complete	<b>104009</b>
2	Spout, complete	<b>310467</b>
1	Power board	<b>104011</b>
1	Portafilter support, service pack	<b>306719</b>
1	Hybridkit for service partner	<b>700243</b>
1	Hybridkit for customer	<b>700245</b>
1	Portafilter lighting set, 4x	<b>700086</b>

## **K30 TWIN 2.0 HYBRID** BASIC STOCK PROPOSAL CLEANING PROCESS

---

### **1. CLEANING:**

Always unplug the coffee grinder before cleaning.

- Apply dry cleaning only. If necessary use suitable mild „dish“ washer detergent
- No alkaline cleaning agent must be used for cleaning (affects-flavour)
- Do not spray coffee grinder with water and/or steam (risk of short circuit)
- Clean your grinder periodically, at least once a week.
- Please use MAHLKÖNIG GRINDZ™

#### **Cleaning of housing:**

- Use paper towel along with mild dish washer detergent to clean the housing, cover lid and inside the hopper

#### **Cleaning of spout tube:**

- Use a vacuum cleaner to exhaust the discharge tube. The use of brushes can lead to the damage of the built-in flappers resulting in an inaccurate grinding result.

Periodic checking of the grinder, burrs and grinding quality must only be performed by competent service personnel and/or trained staff.

### **2. ROUTINE CHECK:**

#### **Indications:**

- Reduction of the output of the grinder.
- Temperature increase of the ground coffee
- Inconsistent grind
- Increased amount of dust
- Grinder clogs more often

### **3. MAINTENANCE:**

#### **Short-term maintenance every 2 weeks**

- Outside cleaning including the hopper
- Use GRINDZ™

#### **Long-term maintenance once a year**

- Thorough cleaning of the grinder including the opening of the grinder housing and removing of all coffee residues
- Change of burrs
- Checking calibration and re-calibrate, if necessary



**Hemro International AG**

Längenstrasse 34 | 8184 Bachenbülach, Schweiz

T: +41 44 864 18 00 | F: +41 44 864 18 01

info@hemrogroup.com | www.hemrogroup.com